

Open Frame

	25W	40W	60W	100W	150W	180W	200W	250W	300W	400W
5V	●	●●●●	●	●						
12V	●	●	●	●	●	●	●	●	●	●
15V			●	●	●		●		●	●
18V				●	●		●			●
19V	●		●		●					
24V	●	●	●	●	●	●	●	●	●	●
36V			●	●	●		●		●	●
48V		●	●	●	●	●	●			●
54V			●	●	○	○				

● Available or in development ○ Planning

FSPxxx-10NAAB



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP025-10NAAB-05	25W	5V	5.0A	Full Range	96.0 x 40.0 x 28.5
FSP030-10NAAB-12	30W	12V	2.5A	Full Range	96.0 x 40.0 x 28.5
FSP030-10NAAB-24	30W	24V	1.3A	Full Range	96.0 x 40.0 x 28.5

FSP042-xKxx



Model	Watts	Output1		Output2		Output3		Input Voltage	Dimension(mm)
		V1	A1	V2	A2	V3	A3		
FSP042-1K00	40W	5V	8A					Full Range	101.6*50.8*30
FSP042-1K20	42W	12V	3.5A					Full Range	101.6*50.8*30
FSP042-1K30	45W	15V	3A					Full Range	101.6*50.8*30
FSP042-1K40	48W	24V	2A					Full Range	101.6*50.8*30
FSP042-1K80	48W	48V	1A					Full Range	101.6*50.8*30
FSP042-2K30	40W	5V	6A	12V	2A			Full Range	101.6*50.8*30
FSP042-2K50	40W	5V	6A	24V	1A			Full Range	101.6*50.8*30
FSP042-3K10	40W	5V	6A	12V	2A	-12V	0.3A	Full Range	101.6*50.8*30
FSP042-3K20	40W	5V	6A	15V	1.5A	-15V	0.3A	Full Range	101.6*50.8*30
FSP042-3K90	40W	5V	6A	24V	1A	-12V	0.3A	Full Range	101.6*50.8*30

Open Frame

FSP045-Pxx-xxN



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP045-P24-12N	45W	12V	5.0A	90~264V	101.6*50.8*30
FSP045-P24-24N	45W	24V	1.88A	90~264V	101.6*50.8*30
FSP045-P24-48N	45W	48V	0.94A	90~264V	101.6*50.8*30
FSP045-P24-54N	45W	54V	0.84A	90~264V	101.6*50.8*30

FSP060-xKxx



Model	Watts	Output1		Output2		Output3		Input Voltage	Dimension(mm)
		V1	A1	V2	A2	V3	A3		
FSP060-1K00	55W	5V	11A					Full Range	101.6*50.8*30
FSP060-1K20	60W	12V	5A					Full Range	101.6*50.8*30
FSP060-1K30	64W	15V	4.3A					Full Range	101.6*50.8*30
FSP060-1K40	64W	24V	2.7A					Full Range	101.6*50.8*30
FSP060-1K80	64W	48V	1.35A					Full Range	101.6*50.8*30
FSP060-2K30	55W	5V	6A	12V	3A			Full Range	101.6*50.8*30
FSP060-2K50	55W	5V	8A	24V	1.5A			Full Range	101.6*50.8*30
FSP060-3K10	55W	5V	6A	12V	3A	-12V	0.5A	Full Range	101.6*50.8*30
FSP060-3K13	37.5W	3.3V	6A	5V	3A	12V	0.5A	Full Range	101.6*50.8*30
FSP060-3K15	37.5W	3.3V	1.5A	5V	6A	12V	0.5A	Full Range	101.6*50.8*30
FSP060-3K20	55W	5V	6A	15V	2.4A	-15V	0.5A	Full Range	101.6*50.8*30
FSP060-3K90	55W	5V	6A	24V	1.5A	-12V	0.5A	Full Range	101.6*50.8*30

FSP065-Pxx-xxN



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP065-P24-12N	65W	12V	5.4A	90~264V	101.6*50.8*30
FSP065-P24-24N	65W	24V	2.7A	90~264V	101.6*50.8*30
FSP065-P24-48N	65W	48V	1.35A	90~264V	101.6*50.8*30
FSP065-P24-54N	65W	54V	1.2A	90~264V	101.6*50.8*30

FSP100-xKxx



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP100-1K00	100W	5V	20A	Auto range	101.6*50.8*32
FSP100-1K20	100W	12V	8.34A	Auto range	101.6*50.8*32
FSP100-1K30	100W	15V	6.7A	Auto range	101.6*50.8*32
FSP100-1K31	100W	18V	5.56A	Auto range	101.6*50.8*32
FSP100-1K40	100W	24V	4.2A	Auto range	101.6*50.8*32
FSP100-1K50	100W	28V	3.57A	Auto range	101.6*50.8*32
FSP100-1K70	100W	36V	2.78A	Auto range	101.6*50.8*32
FSP100-1K80	100W	48V	2.1A	Auto range	101.6*50.8*32

FSP150-K24



New
New
New
New
New
New
New


Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP150-K24-12	150W	12V	12.5A	Full Range	101.6 x 50.8 x 33.0
FSP150-K24-15	150W	15V	10.0A	Full Range	101.6 x 50.8 x 33.0
FSP150-K24-18	150W	18V	8.3A	Full Range	101.6 x 50.8 x 33.0
FSP150-K24-24	150W	24V	6.3A	Full Range	101.6 x 50.8 x 33.0
FSP150-K24-30	150W	30V	5.0A	Full Range	101.6 x 50.8 x 33.0
FSP150-K24-36	150W	36V	4.2A	Full Range	101.6 x 50.8 x 33.0
FSP150-K24-48	150W	48V	3.1A	Full Range	101.6 x 50.8 x 33.0

FSP060-1Sxx



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP045-1S35-05	45W	5V	9.0A	Full Range	127.0x76.2x27.0
FSP060-1S35-05	60W	5V	12.0A	Full Range	127.0x76.2x27.0
FSP060-1S35-12	60W	12V	5.0A	Full Range	127.0x76.2x25.0
FSP060-1S35-19	60W	19V	3.15A	Full Range	127.0x76.2x25.0
FSP060-1S35-24	60W	24V	2.5A	Full Range	127.0x76.2x25.0
FSP060-1S35-36	60W	36V	1.6A	Full Range	127.0x76.2x25.0
FSP060-1S35-48	60W	48V	1.25A	Full Range	127.0x76.2x25.0
FSP060-1S35-54	60W	54V	1.11A	Full Range	127.0x76.2x25.0

FSP100-1Bxx



FSP100-1B01-12	100W	12V	8.3A	Auto range	127.0x76.2x32.0
FSP100-1B01-24	100W	24V	4.16A	Auto range	127.0x76.2x32.0
FSP100-1B01-36	100W	36V	2.78A	Auto range	127.0x76.2x32.0
FSP100-1B01-48	100W	48V	2.1A	Auto range	127.0x76.2x32.0
FSP100-1B01-54	100W	54V	1.85A	Auto range	127.0x76.2x32.0

FSP150-1Hxx




Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP150-1H35-12	150W	12V	12.5A	Full Range	127.0x76.2x31.6
FSP150-1H35-19	150W	19V	7.9A	Full Range	127.0x76.2x31.6
FSP150-1H35-24	150W	24V	6.3A	Full Range	127.0x76.2x31.6
FSP150-1H35-36	150W	36V	4.1A	Full Range	127.0x76.2x31.6
FSP150-1H35-48	150W	48V	3.1A	Full Range	127.0x76.2x31.6

FSP180-1Hxx



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP180-1H35-12	180W	12V	15.0A	Full Range	127.0x76.2x31.6
FSP180-1H35-24	180W	24V	7.5A	Full Range	127.0x76.2x31.6
FSP180-1H35-48	180W	48V	3.8A	Full Range	127.0x76.2x31.6

FSP202-1Kxx(B/C)



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP202-1K20	200W	12V	16.67A	Auto range	127*76*38.8
FSP202-1K30	200W	15V	13.34A	Auto range	127*76*38.8
FSP202-1K31	200W	18V	11.12A	Auto range	127*76*38.8
FSP202-1K40	200W	24V	8.34A	Auto range	127*76*38.8
FSP202-1K50	200W	28V	7.15A	Auto range	127*76*38.8
FSP202-1K70	200W	36V	5.56A	Auto range	127*76*38.8
FSP202-1K80	200W	48V	4.17A	Auto range	127*76*38.8

FSP060-1xNBAB-xx



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP060-10NBAB-12	60W	12V	5.0A	Full Range	129.0 x 98.0 x 38.0
FSP060-10NBAB-15	60W	15V	4.0A	Full Range	129.0 x 98.0 x 38.0
FSP060-10NBAB-24	60W	24V	2.5A	Full Range	129.0 x 98.0 x 38.0
FSP060-12NBAB-12	60W	12V	5.0A	Full Range	129.0 x 98.0 x 38.0
FSP060-12NBAB-15	60W	15V	4.0A	Full Range	129.0 x 98.0 x 38.0
FSP060-12NBAB-24	60W	24V	2.5A	Full Range	129.0 x 98.0 x 38.0

FSP300-K36-xxx



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP300-K36-12B	300W	12V	25A	Auto range	127*76*38.8
FSP300-K36-15B	300W	15V	20A	Auto range	127*76*38.8
FSP300-K36-19B	300W	19V	15.8A	Auto range	127*76*38.8
FSP300-K36-24B	300W	24V	12.5A	Auto range	127*76*38.8
FSP300-K36-30B	300W	30V	10A	Auto range	127*76*38.8
FSP300-K36-36B	300W	36V	8.34A	Auto range	127*76*38.8
FSP300-K36-48B	300W	48V	6.25A	Auto range	127*76*38.8
FSP300-K36-12C	300W	12V	25A	Auto range	127*76*38.8
FSP300-K36-15C	300W	15V	20A	Auto range	127*76*38.8
FSP300-K36-19C	300W	19V	15.8A	Auto range	127*76*38.8
FSP300-K36-24C	300W	24V	12.5A	Auto range	127*76*38.8
FSP300-K36-30C	300W	30V	10A	Auto range	127*76*38.8
FSP300-K36-36C	300W	36V	8.34A	Auto range	127*76*38.8
FSP300-K36-48C	300W	48V	6.25A	Auto range	127*76*38.8

FSP400-1Kxx(B/C)



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP400-1K20x	400W	12V	25A	Auto range	101.6x177.8x40
FSP400-1K30x	400W	15V	20A	Auto range	101.6x177.8x40
FSP400-1K31x	400W	18V	16.67A	Auto range	101.6x177.8x40
FSP400-1K40x	400W	24V	12.5A	Auto range	101.6x177.8x40
FSP400-1K50x	400W	28V	10.72A	Auto range	101.6x177.8x40
FSP400-1K70x	400W	36V	8.34A	Auto range	101.6x177.8x40
FSP400-1K80x	400W	48V	6.25A	Auto range	101.6x177.8x40

FSPxxx-1FUx



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP200-1FUB-24	200W	24V	8.3A	Full Range	201.5x105.0x40.5
FSP200-1FUB-36	200W	36V	5.55A	Full Range	201.5x105.0x40.5
FSP200-1FUB-48	200W	48V	4.16A	Full Range	201.5x105.0x40.5
FSP200-1FUA-12	200W	12V	16.7A	Full Range	214.5x120.4x40.5
FSP250-1FUA-24	250W	24V	10.4A	Full Range	214.5x120.4x40.5
FSP250-1FUA-12	250W	12V	20.8A	Full Range	214.5x120.4x40.5
FSP300-1FUA-24	300W	24V	12.5A	Full Range	214.5x120.4x40.5
FSP400-1FUC-24	400W	24V	16.7A	Full Range	277.5x125.0x40.5
FSP400-1FUC-36	400W	36V	11.11A	Full Range	277.5x125.0x40.5
FSP400-1FUC-48	400W	48V	8.3A	Full Range	277.5x125.0x40.5

FSP200-1B02-xx



Model	Watts	Output Voltage	Output Current	Input Voltage	Dimension(mm)
FSP200-1B02-24	200W	24V	8.4A	Full Range	201.5x105.0x40.5
FSP200-1B02-36	200W	36V	5.2A	Full Range	214.5x120.4x40.5
FSP200-1B02-48	250W	48V	4.2A	Full Range	214.5x120.4x40.5

Mini ITX (DC-DC)

67W - 150W



Model	Watts		+3.3V	+5V	+12V	-12V	+5Vsb	Input Voltage	Dimension(mm)
FSP067-5DD01	67W	Min.	0A	0A	0A	0A	0A	12VDC	141*43*22.1
		Max.	3A	3A	3A	0.1A	1A		
FSP067-5DE01(12)	67W	Min.	0A	0A	0A	0A	0A	12VDC	144*30*33
		Max.	3A	3A	3A	0.1A	1A		
FSP085-5DD01	85W	Min.	0A	0A	0A	0A	0A	12VDC	141*43*22.1
		Max.	5A	6A	4A	0.1A	1.5A		
FSP100-5DD01	100W	Min.	0A	0A	0A	0A	0A	12VDC	141*43*22.1
		Max.	5A	6A	4A	0.1A	1.5A		
FSP100-5DE01(12)	100W	Min.	0A	0A	0A	0A	0A	12VDC	144.25*30*30
		Max.	5A	6A	4A	0.1A	1A		
FSP130-5DD01	130W	Min.	0A	0A	0A	0A	0A	12VDC	141*43*22.1
		Max.	7A	7A	6A	0.1A	1.5A		
FSP150-5DD01	150W	Min.	0A	0A	0A	0A	0A	12VDC	141*43*22.1
		Max.	7A	7A	7A	0.1A	1.5A		

Mini ITX (AC-DC)

55W - 150W



Model	Watts		+3.3V	+5V	+12V	-12V	+5Vsb	Input Voltage	Dimension(mm)
FSP055-50LM	55W	Min.	0.6A	1.0A	0.8A	0A	0A	Full Range	180*50*40
		Max.	4A	7A	3.5A	0.1A	1A		
FSP100-50NCAB	100W	Min.	0.2A	0.5A	1A	0A	0A	Full Range	180*50*40
		Max.	8A	10A	7.5A	0.5A	2A		
FSP130-50LM	130W	Min.	0.3A	0.5A	1A	0A	0A	Full Range	180*50*40
		Max.	8A	10A	8A	0.3A	1.5A		
FSP150-50LM	150W	Min.	0.3A	0.5A	1A	0A	0A	Full Range	180*50*40
		Max.	8A	10A	10A	0.3A	2A		